SPECIFICATION TECHNICAL DATA SHEET

500W Outdoor Power Supply



CET-DY500

2 > Product Specification

1 > General Performance

All in one - outdoor power station

Sattery capacity:126000mAh (403.2Wh)

Charging methods: adapter charging/car charging/solar charging

♦ Battery Life:The portable power station is designed to retain up to 80% of its original capacity at 2000 complete charge cycles when operating under normal conditions.

Output Ports:USB Output Port,Type-C PD Output Port,DC 12V 5521 Output Port,DC12V Cigarette Lighter Output Port,AC Output Port

		Output	
AC Output	Rated Voltage	AC110V±10% or AC220V±10%	
	Rated Power	500W	
	Peak Power	1000W	
	Overload Capability	500W≤load<600W	
	Frequency	50/60Hz(Adjustable)	
DC Output(Cigarette Lighter)	Rated Voltage	12.5V±5%	
	Rated Current	10A Max	
DC Output(5521)	Rated Voltage	12.5V±5%	
	Rated Current	10A Max	
USB-A Output	Rated Voltage	5V-12V	
	Rated Current	24W Max	
USB-C Output	Charging Agreement	PD (60W)	
	Rated Output	5V, 9V ,12V, 15V, 20V	
LED Lighting	While the "POWER' button is on, press the LED light button in turn, the order of LED light will be: Micro bright hullbrightturn off SOS Light : Double-Press the LED button and the SOS light will be turned on.		
		Input	
Input		DC 12-24V	
Input Power		90W (or 150W MAX optional)	
		Battery	
Rated Capacity		403.2Wh	
Battery Cell Type		Lithium iron phosphate (LiFePO4)	
BMS Safety System		Yes	
		General	
Storage Enviroment		14 7.449 7	
Working Temperature		32 7 413 7	
Product Size		267*220*170mm	
Product Net weight		5.8kg	
Certificates		1.CE 2.FCC 3.UL 4.RoHS 5.PSE 6.UN38.3 7.MSDS	



SPECIFICATION TECHNICAL DATA SHEET

3 > Product Introduction



4 > Packing Information

500W Portable Power Station×1 AC Adaptor (Including AC Charging Cable)×1 Cigarette Lighter Cable ×1 DC to MC4 Cable x 1 User Manual x1 ิด 2 6 4 Item Quantity G.W / CTN Carton Size CET-DY500 2 PCS/CTN 16.7 kg 515*330*310

5 > Warranty (1-Year-Limited)

The manufacturer's warranty is void under the following circum	
stances but not limited to:	
Improper or inadequate maintenance or modification.	Accident, misuse, abuse, contamination, or other external ca
The use of unspecified adapter and accessories.	O Damages that occurs as a result of one's failure to follow the

6 > Company Information

Camel Electronic Technology Co., Ltd.

Shenyang Office: No. 741-12 Shenying Street, Hunnan District, Shenyang City, Liaoning Province, China

Guangzhou Office: No.178 Longtang Middle Street, Zhongluotan, Baiyun District, Guangzhou City, Guangdong Province, CN

Email: info@camelet.com

Official Website: https://www.camelet.com



For reference only, the actual product specifications prevail.

instructio